

Thank you for purchasing the Bellari RPV565. We spent a considerable amount of time designing and developing the RPV565. We hope you enjoy using the RPV565, and that it makes listening to your music collection rewarding. We sincerely appreciate the opportunity to build a product for you and participate in your love of quality music and sound. We love what we do and we're happy to help. All Bellari products are hand built in Salt Lake City, Utah by people who care about high quality music.

What's in the box?

- 1 - Made in USA RPV565
- 1 - 15V power supply PN PS27s
- 1 - Remote control
- 1 - This owners manual



RPV565 DAC Preamplifier

SPECIFICATIONS

Input Impedance:	10K ohms
Max Output Gain:	9.8 dB
THD:	0.05%
S/N Ratio:	103 dB, un-weighted
Frequency Response:	11 Hz - 104 KHz
Crosstalk:	-75 dB
Output impedance:	100 Ohms
Digital topology:	Multi-bit Delta-Sigma Modulator
Sample Frequency Range:	32 kHz to 192 kHz
Conversion:	24-bit sampling
Output Connector:	RCA Stereo
Input Connectors:	1: 1/8" TRS Stereo jack 2: RCA Stereo jacks 1: Optical input - Toslink 1: COAX Digital input
PWR:	15 VDC, 500 mA; Part number PS27s
Size:	5.5"w x 1.5"h x 3.5"d
Weight:	.95 lb.

Connection guide

Volume control will adjust the level of RCA output.

Pushing the knob in will activate muting of the output signal.

IR sensor for remote.

Selector switch for channel output selection.

Level display Indicates the output volume level. Will also indicate when unit is muted either with the remote or mute activation with the front panel Volume control.

IN 4 on the front is a 3.5mm (1/8") stereo input. It is a great way to plug your phone into your system without needing access to the back of the unit.



Channel 2 and 3 inputs. Active when selector switch is in 2 or 3 setting.

DC jack for connection to the included power supply

RCA Stereo output for connection to your preamplifier, amplifier or other device.

COAX Digital input. Active when selector switch is in DAC setting.

Digital Optical input. Active when selector switch is in DAC setting.

Remote: Requires 2 AAA batteries (not included)

OFF/ON: For muting output of unit. Press once to mute press again to activate output.

+ and - For volume control

