



RA900 Power Amplifier

The RA900 Power Amplifier is a two channel amp with two 410 watt RMS - 4 ohm outputs via 1/4" jacks or 5-way binding posts. It may be bridged and connected to a 4 or 8 ohm load supplying up to 1100 Watts or 850 Watts respectively. The unit is housed in a painted steel chassis and includes a special high performance transformer, and a fused power line.

The RA900 is ideal for DJs, musicians, or other sound reinforcement applications like powering front-of-house speakers or monitors.

SPECIFICATIONS

Power Output, Stereo:	570 W RMS/ch. 2Ω 410 W RMS/ch. 4 Ω 260 W RMS/ch. 8 Ω
Bridged:	1100 Watts RMS 4 Ω 850 Watts RMS 8 Ω
Input Connectors:	1/4" TRS balanced and XLR balanced
Output Connectors:	1/4" and 5-way binding posts
Sensitivity:	0.9 V rms 0 dB V
THD:	<.05% (20Hz - 20 kHz) @ rated output, 8 Ω)
Frequency response:	@ 1 Watt rms 8 Ω ; 10Hz to 40kHz @ rated output, 8 Ω ; 20Hz to 20kHz
Hum and Noise:	100 dB, unweighted
Power Consumption:	7A and 120 VAC
Cooling System:	2 speed fan
Transformer:	Toroidal
Size:	19" x 3.5" x 15.9" (48.3 x 8.8 x 40.5 cm)
Weight:	31 lbs (14 kg)



ROLLS Coporation
5143 South Main Street, Salt Lake City, UT, 84107
(801) 263-9053 FAX (801) 263-9068
rollsrfx@rolls.com • www.rolls.com